


## LED luminaire Emergency conversion kit - Max.50W



### Product code:

Reference: BATERYPCTMBW

### Technical specifications:

REFERENCE: BATERYPCTMBW  
Rated Power : 3W-50W  
Nominal Voltage: DC18V-175V  
Construction Material: Thermoplastic  
Certifications: CE - ROHS  
IP : IP20  
Dimensions (mm): 140x55x33mm  
Frequency (Hz): 50/60Hz  
Temperature Range (°C): -15° + 50°  
Other Information: Battery 3.7V / 2.5Ah  
Material of the Battery: LiFePO4 - Lithium-Ferrophosphate -LPF  
Download Time: 50W: 50 minutes - 40w: 60 minutes - 30w: 75 minutes - 20w: 90 minutes  
Energy Rating (2021-UE-2019/2015): A+  
Warranty Years: 2

### Product short description:

**CONVERTS ALL TYPES OF LED LUMINAIRE - WITH DRIVER - IN EMERGENCY.** With the 2500mAh emergency battery you will be able to convert any LED luminaire into an emergency. Its operation is by regulating the luminaire to 30% where you install it automatically. **Maximum of 50W. (Not suitable for Driverless products).**

### Product description:

The battery has 2500 mAh (2.5Ah) of a range that depends on the consumption according to the watts of the luminaire where it is installed. The luminaire will regulate the luminous flux to 30% of its total power, resulting in a minimum duration of:

- 50W: Duration 50 minutes
- 40w: Duration 60 minutes
- 30w: Duration: 75 minutes
- 20w: Duration 90 minutes

The battery is installed by powering the luminaire's LED driver and connecting to the electrical network.

### Additional images:



# Technical Datasheet

---