

## LED Tracklight 10W FENIX - BLACK - 3-PHASE Rails - CRI+93



### Product code:

Reference: TRB10W-BLACK

### Technical specifications:

REFERENCE: TRB10W-BLACK  
Rated Power : 10W  
Nominal Voltage: 175-265V  
Colour: 3000K - 4000K  
CRI - Chromatic Rendiment Index: 93  
Construction Material: Aluminium +P MMA  
Luminosity-Lm: 4800  
Number & Type of LEDs: COB BRIDGELUX CHIP 2630 DS-C30  
Beam Angle (°): 24°  
Luminous diodo LED (Lm/W): 130Lm/W  
Luminous Efficiency (Lm/W): 100 Lm/W  
Certifications: CE - ROHS  
IP : IP20  
Diode Life Expectancy (H): 35.000  
Frequency (Hz): 50/60Hz  
Temperature Range (°C): -20° ~ +40°  
On/Off Cycles: 100.000  
Starting Time (s): 0,2s  
Other Information: Painting: AkzoNobel Interpon 600 C33883  
Energy Rating (2021-UE-2019/2015): A+  
Warranty Years: 3

### Product short description:

Our **10W -FENIX- 3-PHASE -Black- LED tracklight** incorporates a **BRIDGELUX COB chip**, with a very high chromatic resolution index of over +93, which makes the quality of the light unbeatable, and the realism of the colours almost perfect for highlighting specific elements. **24°** angle.

### Product description:

LED Tracklight 10W FENIX - BLACK - 3-PHASE Rails - CRI+93

The **LED tracklight -FENIX- BRIDGELUX Chip** of 10w is characterized because it has a design that will combine with any style and excellent performance.

The **FENIX LED tracklight** has **BRIDGELUX Chip** is ideal for illuminating any place you want to highlight, it is also perfect for situations in spaces that are looking for class and distinction in its lighting network also you have it in different temperatures **3000k and 4000k**.

Its Black design is ideal for creating minimalist environments while highlighting the spaces you need to highlight. Its installation is simple to be placed in single-phase rail, now the decoration is in your hands and in the easiest way.

This product has been manufactured for special indoor use, hence its **IP20** protection.

Our **FENIX LED tracklight** emits 1000 lumens (COB BRIDGELUX CHIP 2630 DS-C30) and saves up to 90% on our bill. The spotlight is able to withstand voltage from **175V to 265V**.

Uses of the LED **Tracklight** 10W FENIX -BLACK- 3-PHASE Rails CRI+93 - 24° - Bridgelux Chip:

- Shop windows
- Offices
- Showcases
- Stores
- Art galleries
- Museums

In FactorLED we ensure that our products have **QUALITY** guarantee and offer all the necessary elements for **DISTRIBUTION, IMPORT or WHOLESale**, including the technical data sheet of each LED product.

**Additional images:**

